

DC DRIVE - DCD96 / DCD72



DCD96
[96*96*85]



DCD72
[72*72*110]

Protections & Features

- Heavy-Duty line supresors for Mains Power Fluctuations and Noise
- In-Built Soft Start
- Motor Overload Protection by adjustable Current Limit & Current Trip
- Adjustable Min and Max speed at back side
- Front Panel Motor On Indication
- Front Panel ON-OFF switch and Speed set Potentiometer
- Front panel digital display with adjustment on back side
- Easily replaceable Fuses and terminals for connections at the backside
- 'Remote On-Off'[Control On-Off] provision for frequent Motor On-Off operation

Technical Specifications:-

Housing Front Panel mounting type, Powder coated MS Enclosure.

Size[mm] 96 X 96 X 85 or 72 X 72 X 110mm

Cutout[mm] 92 x 92 or 68 X 68

Ratings

- I/P Supply : 230V AC, +/- 10%, 50 Hzs.
- Armature O/P : 0V - 180V DC variable.
- Power : Up to 1HP PMDC/Shunt motor.
- Display : 31/2 digit. Max display=1999 count.

Note: The display can be viewed with any required value from 000 to Max 1999 count. This reading will be directly proportional to the motor output voltage and not the RPM



Manufactured by :

Cogent Controls

205, Vinay Industrial. Estate., Chincholi Bunder Link Road,
Malad-W, Mumbai - 400 064 Tel: 28750421/20
Email: cogentcontrols@gmail.com /info.cogentcont@gmail.com
Website : www.cogentcontrols.com